



TESFA/S/ST24.2/0

- 1 cable entries M 16 x 1.5
- with fixed switching angle
- 1 connector M12, 8-pole
- Metal enclosure
- Good resistance to oil and petroleum spirit
- For left or right hinged doors
- 141 mm x 115 mm x 21,5 mm
- Simple mounting, [REDACTED]
[REDACTED] (30 ... 60 mm)

Data

Ordering data

eCl@ss number, Version 9.0	27-27-06-09
eCl@ss number, Version 11.0	27-27-06-09
ETIM number, version 6.0	EC002591
ETIM number, version 7.0	EC002591

Approval - Standards

Certificates	IFA
	cULus
	CCC
	EAC

General data

Standards	EN 60947-5-1
	BG-GS-ET-15

Enclosure material	Zinc die-cast
Material of the contacts, electrical	Silver-nickel alloy 10
Colour of the housing	Black
Gross weight	616 g

General data - Features

Mounting outside	Yes
Alignment aid	Yes
Number of auxiliary contacts	2
Number of safety contacts	2

Safety appraisal

Standards	EN ISO 13849-1
Mission Time	20 Year(s)

Safety appraisal - Safety outputs

B10d Normally-closed contact (NC)	2,000,000 Operations
B10d Normally open contact (NO)	1,000,000 Operations

Mechanical data

Mechanical life, minimum	1,000,000 Operations
Positive break angle	14 °
Opening angle	180°

Mechanical data - Connection technique

Terminal Connector	Plug-in connection, top
--------------------	-------------------------

Mechanical data - Dimensions

Length of sensor	21.5 mm
Width of sensor	141 mm
Height of sensor	115 mm

Ambient conditions

Degree of protection	IP65
Ambient temperature, minimum	-25 °C
Ambient temperature, maximum	+65 °C

Ambient conditions - Insulation value

Rated insulation voltage U_i	250 V
Rated impulse withstand voltage U_{imp}	0.8 kV

Electrical data

Thermal test current	2.5 A
Utilisation category AC-15	230 VAC
Utilisation category AC-15	2 A
Utilisation category DC-13	24 VDC
Utilisation category DC-13	1 A
Switching element	NO contact, NC contact
Switching principle	Creep circuit element
Switching frequency	1,200 /h

Notes

Note (General)	Caution! According to EN 60204-1, the versions with connector must only be used in PELV circuits.
----------------	---

can be found in the manual. Technical amendments and errors possible.

Generated on: 11/9/2021, 10:25 AM