#### **CDA** 16 poles + 🕀 16A - 250V

enclosures: size "66.16"	page:
IL-BRID	378 - 382
CZ7 IP67, single lever	385
W-TYPE for aggressive environments	520
E-Xtreme® corrosion proof	541
EMC	577
panel supports:	page:
COB + adaptor	652 - 654

inserts. screw terminal connection





screw terminal connection

CDA

# description

part No. CDAF 16

CDAM 16



female inserts with female contacts male inserts with male contacts

## - characteristics according to EN 61984:

- 16A 250V 4kV 3
- 16A 230/400V 4kV 2
- ະ 🕰 us (UL for USA and Canada), 👀 🗪

## VERITAS ERC certified

- rated voltage according to UL/CSA: 600V
  insulation resistance: ≥ 10 GΩ
- ambient temperature limit: -40 °C ... +125 °C
- made of self-extinguishing thermoplastic resin UL 94V-0 - mechanical life: ≥ 500 cycles
- contact resistance:  $\leq 1 \text{ m}\Omega$
- according to recommendations EUROMAP N° 13 / N° 14.1
- for max. current load see the connector inserts derating diagram below; for more information see page 28



Μ

### contacts side (front view)

ald ald
---------

- inserts with pressure plate for conductors cross-sections:

- 0.5 4 mm<sup>2</sup> AWG 20 12

- conductors stripping length: 7 mm - terminal screw torque: 0,5 Nm (4.4 lb.in), for more information see page 20 and 21

1) for unprepared conductors





#### CDAF 16 X CDAM 16 X

part No.

inserts.



### contacts side (front view)



- inserts without pressure plate for prepared

conductors with cross-sections: 0,25 - 2,5 mm<sup>2</sup> - AWG 24 - 14

- terminal screw torque: 0,5 Nm (4.4 lb.in), for more information see page 20 and 21

<sup>2)</sup> for conductors with end sleeve ferrule







100